

Transverse electrokinetic and microfluidic effects in micro-patterned channels: lubrication analysis for slab geometries

Armand Ajdari

Laboratoire de Physico-Chimie Théorique, Esa CNRS 7083, ESPCI, 10 rue Vauquelin, F-75231 Paris Cedex 05, France
submitted to Phys. Rev. E. dec. 2000

Off-diagonal (transverse) effects in micro-patterned geometries are predicted and analyzed within the general frame of linear response theory, relating applied pressure gradient and electric field to flow and electric current. These effects could contribute to the design of pumps, mixers or flow detectors. Shape and charge density modulations are proposed as a means to obtain sizeable transverse effects, as demonstrated by focusing on simple geometries and using the lubrication approximation.

PACS: 47.65.+a ; 83.60.Np, 85.90.+h

I. INTRODUCTION

The development of microfluidic devices and studies has prompted the quest for various strategies to achieve pumping in micro-geometries [1–7]. Pressure driven flows is the first obvious possibility, with the inconvenience of important Taylor dispersion due to the parabolic flow profiles [8]. Electro-osmosis has been proposed and developed as a way to generate almost perfect plug-flows, thereby reducing dispersion in various devices, which results in limited dilution of samples, and processability for separation purposes [7]. This solution implies relatively high voltages applied between the ends of the channels.

In this paper, micro-patterned channels are proposed as a way to generate a large class of effects using pressure gradients or electric fields. In particular various off-diagonal effects can be obtained in which a cause along one direction leads to a measurable or useful effect in a perpendicular direction. These effects could be exploited for the realization of transverse pumps, mixers, flow detectors, etc ... A proposed pattern is the periodic modulation of the shape of the channels, which can be improved by a combined modulation of the surface charge density. (in line with an earlier study that dealt with transverse electro-osmosis on such surfaces [9]). The aim is here to explore the ensemble of transverse effects achievable.

To reach this goal, the linear response regime is considered, which permits the use of a very general Onsager formalism, to relate fields (pressure and electric potential gradients) to fluxes (hydrodynamic flow and electric current). For the sake of clarity, we further restrain our analysis to a simple class of geometries, with the fluid confined between two parallel plates, homogeneously and periodically patterned (Fig. 1). Parallel walls may be present so as to form a capillary.

The geometry and the matrix representation of the linear Onsager formalism are proposed in Section II. In section III the off-diagonal effects are described at a phenomenological level, for the case of passive walls (a few situations where electrodes are embedded in the walls are considered in Appendix 1, and the corresponding wall generated effects analyzed). In section IV an ex-




FIG. 1. Slab geometry considered in this paper: Two parallel walls bear on their inner faces periodic micro-fabricated patterns of principal axes x and y . The slab can be limited sideways by walls, the axis of the resulting capillary e_2 at an angle θ with the pattern. From section IV on, we focus on patterns periodic along x and invariant along y .

PLICIT realization is described and estimates for the effects given. The calculations are performed using the lubrication approximation, and assuming weak surface potentials, which gives a convenient analytic handle on these complex systems. Results for sinusoidal modulations of the shape and charge densities are reported in Appendix 2. A brief discussion closes the paper (section V), pointing out directions for future studies.

II. LOCAL LINEAR RESPONSE

We consider the Hele-Shaw quasi-planar geometry of Figure 1, where the two sides of the slab bear patterns of principal axes (x, y) , and set the formalism relating locally 2D fields to 2D fluxes (i.e. integrated over z).

A. In the principal axes (x, y)

In the linear response regime, the 2D currents (hydrodynamic flow $\mathbf{J}$ and electric current $\mathbf{J}_{el}$) are related to the pressure gradient ∇p and to the electrostatic potential gradient $\nabla \phi = -\mathbf{E}$, by a matrix equation [11]:

$$\mathbf{J} = \hat{\mathbf{K}} \cdot (-\nabla p) + \hat{\mathbf{M}} \cdot (-\nabla \phi) \quad (1)$$

$$\mathbf{J}_{el} = \hat{\mathbf{M}} \cdot (-\nabla p) + \hat{\mathbf{S}} \cdot (-\nabla \phi). \quad (2)$$

where the matrices $\hat{\mathbf{F}}$ with F equal to K , M or S are diagonal in the (x, y) basis:

$$\hat{\mathbf{F}} = \begin{pmatrix} F_x & 0 \\ 0 & F_y \end{pmatrix} \quad (3)$$

The permeation matrix $\hat{\mathbf{K}}$ describes the flow induced by pressure differences (the Darcy law in a porous medium). The conduction matrix $\hat{\mathbf{S}}$ relates the electric current to the electric field (the medium's Ohm's law). The matrix $\hat{\mathbf{M}}$ describes the electro-hydrodynamic coupling (so-called electrokinetic effects). In equation (1) it quantifies *electro-osmosis*, i.e. the hydrodynamic flow induced by the electric field. This effect stems from the presence of thin diffuse layers in the vicinity of charged walls where the fluid is non-neutral, and thus dragged by the local electric field. In (2) $\hat{\mathbf{M}}$ measures the electric current induced by the presence of a net hydrodynamic flow. This is due to the convective transport of the above mentioned charged layer which leads to an ionic current. The result is hydrodynamically generated electrostatic potential differences ("streaming potentials") and electric currents ("streaming currents").

Equivalently, the inverse system (the resistance matrix), gives the fields as functions of the currents:

$$-\nabla p = \hat{\mathbf{k}} \cdot \mathbf{J} + \hat{\mathbf{m}} \cdot \mathbf{J}_{\text{el}} \quad (4)$$

$$-\nabla \phi = \hat{\mathbf{m}} \cdot \mathbf{J} + \hat{\mathbf{s}} \cdot \mathbf{J}_{\text{el}}. \quad (5)$$

where the matrices $\hat{\mathbf{k}}$, $\hat{\mathbf{m}}$ and $\hat{\mathbf{s}}$, are diagonal 2x2 matrices of the form (3) with, for $i = x, y$:

$$k_i = S_i / \Delta_i, \quad m_i = -M_i / \Delta_i \quad (6)$$

$$s_i = K_i / \Delta_i, \quad \Delta_i = K_i S_i - M_i^2 \quad (7)$$

B. In an arbitrary (e_1, e_2) coordinate system

All the above is standard in the 1D geometry of cylindrical capillaries, or for homogeneous and isotropic porous media, where K , S and M are scalars. Here, we explore the phenomena occurring in the present 2D geometry with non-equivalent properties along the x and y axes, allowing for the existence of off-diagonal effects. If the pattern is disposed at an angle θ to the measurement geometry, the above linear relations are best expressed in the new system of coordinates related to the basis (e_1, e_2) (Figs. 1 and 2). This leads to 4x4 matrices describing the generalized conductance of the system:

$$\begin{bmatrix} \mathbf{J} \\ \mathbf{J}_{\text{el}} \end{bmatrix} = \begin{bmatrix} \mathbf{K} & \mathbf{M} \\ \mathbf{M} & \mathbf{S} \end{bmatrix} \cdot \begin{bmatrix} -\nabla p \\ -\nabla \phi \end{bmatrix} \quad (8)$$

and its generalized resistance:

$$\begin{bmatrix} -\nabla p \\ -\nabla \phi \end{bmatrix} = \begin{bmatrix} \mathbf{k} & \mathbf{m} \\ \mathbf{m} & \mathbf{s} \end{bmatrix} \cdot \begin{bmatrix} \mathbf{J} \\ \mathbf{J}_{\text{el}} \end{bmatrix} \quad (9)$$




FIG. 2. Top view of the slab geometry of Figure 1

where the 2x2 matrices $\mathbf{K}$, $\mathbf{M}$, $\mathbf{S}$, $\mathbf{k}$, $\mathbf{m}$ and $\mathbf{s}$ are now non-diagonal and given by $\mathbf{F} = \mathbf{R}_\theta \cdot \hat{\mathbf{F}} \cdot \mathbf{R}_\theta^{-1}$, where $\mathbf{R}_\theta$ is the rotation matrix between (x, y) and (e_1, e_2) .

$$\mathbf{R}_\theta = \begin{pmatrix} \cos \theta & -\sin \theta \\ \sin \theta & \cos \theta \end{pmatrix} \quad (10)$$

so that the generic matrix

$$\mathbf{F} = \begin{pmatrix} F_{11} & F_{12} \\ F_{21} & F_{22} \end{pmatrix} \quad (11)$$

is symmetric and given by:

$$\mathbf{F} = \begin{pmatrix} F_x \cos^2 \theta + F_y \sin^2 \theta & (F_x - F_y) \sin \theta \cos \theta \\ (F_x - F_y) \sin \theta \cos \theta & F_y \cos^2 \theta + F_x \sin^2 \theta \end{pmatrix} \quad (12)$$

III. NON-DIAGONAL EFFECTS

Non diagonal or transverse effects (a cause along e_1 induces an effect along e_2 or the reverse) occur if some of the local transverse coefficients K_{12} , M_{12} , or S_{12} are non-zero. From the above geometric formula, this requires $K_x \neq K_y$, $M_x \neq M_y$, or $S_x \neq S_y$, i.e. that the anisotropy in the pattern of the plates has translated into different susceptibilities along the two principal axes x and y .

We postpone to section IV a description of a way to achieve this asymmetry, and start with a generic description of the effects expected if local anisotropy is present.

A. Open homogeneous geometries

In an open homogeneous geometry (no walls in Figure 1), the two simplest situations are the following:

No pressure differences - Then an electric field $\mathbf{E}$ generates an electric current $\mathbf{J}_{\text{el}} = \mathbf{S} \cdot \mathbf{E}$ and an *electro-osmotic* flow $\mathbf{J} = \mathbf{M} \cdot \mathbf{E}$, at finite angles with respect to the

applied field $\mathbf{E}$, if $\mathbf{S}$ and $\mathbf{M}$ are non-diagonal. Explicit ways to obtain non-diagonal electro-osmotic flows were proposed in [9], and are revisited in section IV within a simple lubrication picture.

No electrostatic potential differences - If all potential differences are short-circuited by an appropriate design of electrodes connected by low-resistance wiring, then a pressure gradient creates not only a hydrodynamic flow $\mathbf{J} = \mathbf{K} \cdot (-\nabla p)$, but also an electric current $\mathbf{J}_{\text{el}} = \mathbf{M} \cdot (-\nabla p)$ through the wiring circuit. This current in a simple 1D geometry is called the streaming current. Both hydrodynamic and electric currents are again generically not aligned with the applied pressure gradient.

As this remains formal, geometries are now considered where the fluid is confined to a rectangular channel.

B. Channel with passive walls

Take a channel of length L along e_2 and width d along e_1 , bounded by impermeable walls. We suppose here that no electric current can flow from one side to the other, so both fluxes in direction e_1 are on average zero: $J_1 = 0$ and $J_{\text{el}1} = 0$. Potential differences between the two walls can however be measured using a set of electrodes connected by a high resistance in series with a voltmeter (Fig. 3). In this geometry it is straightforward to quantify the effects generated by a forcing along the length of the channel (direction e_2).

1. Pressure-driven effects

Suppose a pressure drop Δp_2 is applied along the channel so that the average value of $\partial_2 p$ is $\Delta p_2/L$. We furthermore consider that there is no external electrical path connecting the two ends of the channel (in particular the fluid flow does not carry in or out a net current - no streaming current carried by the convection of the neutral fluid at the inlet and outlet of the channel-) so that $J_{\text{el}2} = 0$: any streaming current (along the walls) is compensated by a back-current in the bulk.

The application of the pressure drop Δp_2 then results in longitudinal effects along e_2 : a fluid flow J_2 and a potential drop $\Delta \phi_2$ given by:

$$(-\Delta p_2/L) = k_{22} J_2 \quad (13)$$

$$(-\Delta \phi_2/L) = m_{22} J_2 \quad (14)$$

The potential drop $\Delta \phi_2 = (m_{22}/k_{22})\Delta p_2$ is the classical “streaming potential”, proportional in the simplest cases to the average surface potential of the walls. The flow J_2 is given by a Darcy law modified by electric effects: $J_2 = k_{22}^{-1}(-\Delta p_2/L)$.

More interestingly, transverse effects are also generated in the e_1 direction: a pressure difference Δp_1 and a potential drop $\Delta \phi_1$:




FIG. 3. Passive walls: Neither hydrodynamic flow nor electric current is possible along the e_1 axis. A potential difference $\Delta \phi_1$ can be measured using a high input impedance voltmeter.

$$(-\Delta p_1/d) = k_{12} J_2 = (k_{12}/k_{22})(-\Delta p_2/L) \quad (15)$$

$$(-\Delta \phi_1/d) = m_{12} J_2 = (m_{12}/k_{22})(-\Delta p_2/L) \quad (16)$$

The pressure difference Δp_1 exists if $k_{12} \neq 0$, in which case it indicates that recirculation is taking place in the e_1 direction: the pressure drop along e_2 entrains fluid in the e_1 direction, which, due to the presence of the walls, then has to recirculate. A certain amount of shearing and mixing is thus induced.

The electric potential difference $\Delta \phi_1$ is a “transverse streaming potential” proportional to the non-diagonal electrokinetic coefficient m_{12} . It is a transverse electric measure of the hydrodynamic flow along e_2 . Note that, even if the local off-diagonal coupling m_{12}/k_{22} is large, this potential drop is intrinsically smaller than the streaming potential along the channel by a factor d/L due to the geometry of the system.

2. Electrically-driven effects

Suppose now that an electric current $J_{\text{el}2}$, or an average electric field E_2 , is applied along a channel connected to large open reservoirs so that $\Delta p_2 = 0$.

This yields classical effects along the channel, which are simply Ohm’s law and the “electro-osmotic flow”: a net flow J_2 induced by the electric field:

$$(-\Delta p_2/L) = k_{22} J_2 + m_{22} J_{\text{el}2} = 0 \quad (17)$$

$$(-\Delta \phi_2/L) = m_{22} J_2 + s_{22} J_{\text{el}2} = E_2 \quad (18)$$

The electro-osmotic flow is thus $J_2 = -(m_{22}/k_{22})J_{\text{el}2} = -\frac{m_{22}}{k_{22}s_{22}-m_{22}^2}E_2$ while the resistivity of the channel is

given by $E_2 = (s_{22} - m_{22}^2/k_{22})J_{el2}$.

In addition, transverse effects are generated in the perpendicular e_1 direction: a pressure difference Δp_1 and a potential drop $\Delta\phi_1$.

$$(-\Delta p_1/d) = k_{12}J_2 + m_{12}J_{el2} = \frac{m_{12}k_{22} - k_{12}m_{22}}{s_{22}k_{22} - m_{22}^2}E_2 \quad (19)$$

$$(-\Delta\phi_1/d) = m_{12}J_2 + s_{12}J_{el2} = \frac{s_{12}k_{22} - m_{12}m_{22}}{s_{22}k_{22} - m_{22}^2}E_2 \quad (20)$$

Equation (19) indicates that the electric field E_2 induces an electro-osmotic flow along e_1 (if $m_{12} \neq 0$), which due to the presence of the walls, leads to a pressure difference Δp_1 that induces recirculation of the fluid along e_1 . Again this induces shear and favors mixing. This effect is due both to the non-diagonal permeation (k_{12}) and to transverse electro-osmosis per se (m_{12}).

Equation (20) describes an “electrokinetic Hall effect”: an electric field applied along e_2 results in an electrostatic potential difference along e_1 : it consists of a term due to the anisotropic conductivity (s_{12}) and to transverse streaming current (m_{12}).

C. Comments

Many other geometries can actually be envisaged. In Appendix 1 we consider situations where electrodes are embedded in the walls, which permits, for example, the generation of flow along the channel from transverse potential differences between the walls. Let us stress here a few general points:

- Evaluation of the effect is easy only if the geometry (imposed boundary conditions) permits homogeneous solutions for the gradients and currents. Otherwise one has to solve the 2D conservation equations for the currents.
- This obviously would also be the case with heterogeneous patterns on the plates. We will return to this in the discussion section.
- A more serious (less obvious) problem has to do with electrodes: the specificities of electrochemistry at their surface may require a description in terms of the fluxes of the various ions rather than the simple description in terms of an electric current of Appendix 1, in addition to the many experimental problems involved (surface corrosion, generation of gas bubbles, etc ...).
- In the channel geometries considered here, modifying or controlling the electrical connection between the walls affects the longitudinal coefficients K_{22}, M_{22}, S_{22} (if off-diagonal coefficients are non-zero).

Clearly several coefficients describe the various couplings allowed by symmetry in this linear theory. To give quantitative estimates for these coefficients and thus for the corresponding effects one has to deal with notoriously difficult (even at low Reynolds number) electrohydrodynamic calculations. However a useful guide can be developed using the lubrication approximation, as shown in the next section.




FIG. 4. Geometry considered in Section IV : a) case of a uniform flat system, b) the slip parameters describing electrokinetic effects and the thickness vary along x only.

IV. SPECIFIC CALCULATIONS WITHIN LUBRICATION APPROXIMATION

A. Geometry and approximations

In this section, modulating the shape and the charge density on the plates is proposed as an efficient patterning to obtain transverse effects. Explicit calculations of the matrix coefficients introduced in section II are performed, which provide an estimate of the off-diagonal effects as listed in section III. For the analysis to remain simple, I focus on the specific case where the charge and/or surface pattern is periodic along the direction x and invariant along the perpendicular direction y . To set notations, the channel has a local thickness $h(x) = h_0 + \delta h(x)$, and modulated charge densities $\sigma_1(x)$ on the bottom plate and $\sigma_2(x)$ on the top one (Figure 4). Further, the following assumptions are made:

- (i) the modulation wavelength is larger than the gap so that lubrication approximation holds [10].
- (ii) the ionic strength is high enough for the typical gap thickness h_0 to be much larger than the Debye length $\lambda_D = \kappa^{-1}$,
- (iii) the surface potentials (or charge densities) are weak enough for the double layers to be well described by the Debye-Hückel theory. All effects are calculated to first order in these surface charge densities, so that terms proportional to products of σ_i are neglected altogether. This restriction comes in addition to (and is distinct from) the fact that we focus on the linear response of fluxes to applied fields.

Although these assumptions limit the quantitative precision of the results, they permit analytic calculations and thus a clear discussion of important qualitative features at a reasonably simple level.

B. Flat and uniform surfaces

To get a physical insight, it is useful to start with the simple geometry of uniform flat surfaces (Fig. 4a):

$h(x) = h_0$, σ_1 and σ_2 constant. The computation of electrokinetic effects is then simple (given (ii) and (iii) [12]), and can be found in textbooks (e.g. [11]).

Electro-osmosis - If an electric field E is present in the channel, it will exert a drag on the thin charged Debye layer in the vicinity of the surfaces. The actual no-slip boundary condition for the solvent flow on the real surface of the plates can then be replaced by an electro-osmotic slip velocity $v_i = -\mu_i E$ on plate i , where $\mu_i = \sigma_i \lambda_D / \eta$, and η is the viscosity of water. This leads to a simple flow profile $v_{EO}(z) = -\mu_1 E(1 - 2z/h_0) - \mu_2 E(1 + 2z/h_0)$ and a net electro-osmotic flow through the channel $J_{EO} = -(\mu_1 + \mu_2)h_0 E/2$.

Poiseuille flow - In addition there is naturally the pressure driven flow $v_{Poiseuille} = (z^2 - h_0^2/4)\partial_x p/2\eta$ which gives a current $J_{Poiseuille} = -h_0^3 \partial_x p/12\eta$.

Flow-induced current - This pressure-driven flow induces transport of the charged fluid of the Debye layers. If the local shear rate in the vicinity of the i -th plate is $\dot{\gamma}$, the induced current is (per unit length in the y direction) $J_{eli} = -\sigma_i \lambda_D \dot{\gamma} = -\eta \mu_i \dot{\gamma}$. Given that $\dot{\gamma} = -h_0 \partial_x p/2\eta$, this leads to a total current $J_{elFlow-induced} = (\mu_1 + \mu_2)h_0 \partial_x p/2$. Note that in principle, electro-osmotic flows also induce convective transport of the charged regions, but this effect is then clearly proportional to $\sigma_i \sigma_j$ and neglected here along (iii).

Ohm's law - Of course the flow-induced current is often a minor correction to the main conduction current described by Ohm's law $J_{elOhm} = \sigma_{el} h_0 E$.

Gathering all contributions, we are thus led to a scalar (in this isotropic case) version of equations (1) and (2):

$$J = \frac{h_0^3}{12\eta} \cdot (-\nabla p) - h_0 \frac{\mu_1 + \mu_2}{2} \cdot (-\nabla \phi) \quad (21)$$

$$J_{el} = -h_0 \frac{\mu_1 + \mu_2}{2} \cdot (-\nabla p) + \sigma_{el} h_0 \cdot (-\nabla \phi). \quad (22)$$

The symmetry of the Onsager matrix is here clear.

C. Fields and currents along the modulation direction x

Returning to a channel periodically modulated along x , I consider first the case where the fluxes and gradients are applied along this axis. In this geometry, the currents J_x and J_{elx} are constants, whereas the local values of the pressure gradient $\partial_x p(x)$ and electric field $E_x(x)$ vary (although slowly enough in the lubrication approximation to consider them independent of z).

In the lubrication picture we can transcribe the results of the previous subsection:

$$J_x = \frac{h^3(x)}{12\eta} \cdot (-\partial_x p(x)) - h(x) \frac{\mu_1 + \mu_2}{2} \cdot E_x(x) \quad (23)$$

$$J_{elx} = -h(x) \frac{\mu_1 + \mu_2}{2} \cdot (-\partial_x p(x)) + \sigma_{el} h(x) \cdot E_x(x) \quad (24)$$

Then, neglecting terms proportional to the product of $\sigma_i s$ (or $\mu_i s$), and performing integrals along x over a period of the modulation, gives

$$\begin{pmatrix} \langle -\partial_x p \rangle \\ \langle -\partial_x \phi \rangle \end{pmatrix} = \frac{12\eta}{\sigma_{el}} \begin{pmatrix} \sigma_{el} \langle \frac{1}{h^3} \rangle & \langle \frac{\mu_1 + \mu_2}{2h^3} \rangle \\ -\langle \frac{\mu_1 + \mu_2}{2h^3} \rangle & \frac{1}{12\eta} \langle \frac{1}{h} \rangle \end{pmatrix} \begin{pmatrix} J_x \\ J_{elx} \end{pmatrix} \quad (25)$$

where $\langle f \rangle$ is the average of the function $f(x)$ over a period. With the same approximations, inversion yields:

$$\begin{pmatrix} J_x \\ J_{elx} \end{pmatrix} = \Delta_x \begin{pmatrix} \frac{1}{12\eta} \langle \frac{1}{h} \rangle & -\langle \frac{\mu_1 + \mu_2}{2h^3} \rangle \\ -\langle \frac{\mu_1 + \mu_2}{2h^3} \rangle & \sigma_{el} \langle \frac{1}{h^3} \rangle \end{pmatrix} \begin{pmatrix} \langle -\partial_x p \rangle \\ \langle -\partial_x \phi \rangle \end{pmatrix} \quad (26)$$

with $\Delta_x^{-1} = \langle \frac{1}{h^3} \rangle \langle \frac{1}{h} \rangle$.

D. Fields and currents along the perpendicular direction y

I now take fields and flows along the perpendicular direction y . In an infinite geometry, the electric field E_y and the pressure gradient $\partial_y p$ are independent of x , whereas the currents are modulated along this direction.

$$J_y(x) = \frac{h^3(x)}{12\eta} \cdot (-\partial_y p) - h(x) \frac{\mu_1 + \mu_2}{2} \cdot E_y \quad (27)$$

$$J_{ely}(x) = -h(x) \frac{\mu_1 + \mu_2}{2} \cdot (-\partial_y p(x)) + \sigma_{el} h(x) \cdot E_y \quad (28)$$

Averaging over a period along x here gives:

$$\begin{pmatrix} \langle J_y \rangle \\ \langle J_{ely} \rangle \end{pmatrix} = \begin{pmatrix} \frac{1}{12\eta} \langle h^3 \rangle & -\langle \frac{\mu_1 + \mu_2}{2} h \rangle \\ -\langle \frac{\mu_1 + \mu_2}{2} h \rangle & \sigma_{el} \langle h \rangle \end{pmatrix} \begin{pmatrix} -\partial_y p \\ -\partial_y \phi \end{pmatrix} \quad (29)$$

or upon inversion

$$\begin{pmatrix} -\partial_y p \\ -\partial_y \phi \end{pmatrix} = \Delta_y^{-1} \frac{12\eta}{\sigma_{el}} \begin{pmatrix} \sigma_{el} \langle h \rangle & \langle \frac{\mu_1 + \mu_2}{2} h \rangle \\ \langle \frac{\mu_1 + \mu_2}{2} h \rangle & \frac{1}{12\eta} \langle h^3 \rangle \end{pmatrix} \begin{pmatrix} \langle J_y \rangle \\ \langle J_{ely} \rangle \end{pmatrix} \quad (30)$$

with $\Delta_y^{-1} = \langle h^3 \rangle^{-1} \langle h \rangle^{-1}$.

E. Summary for arbitrary modulations

We can now write down the local coefficients of the response matrix to make the anisotropy in (x, y) explicit. The coefficient of the permeability matrices (section II) giving fluxes as functions of gradients are:

$$K_x = \frac{1}{12\eta} \langle 1/h^3 \rangle^{-1}; \quad K_y = \frac{1}{12\eta} \langle h^3 \rangle \quad (31)$$

$$S_x = \sigma_{el} \langle 1/h \rangle^{-1}; \quad S_y = \sigma_{el} \langle h \rangle \quad (32)$$

$$M_x = -\frac{\langle \frac{\mu_1 + \mu_2}{2h^3} \rangle}{\langle \frac{1}{h^3} \rangle \langle \frac{1}{h} \rangle}; \quad M_y = -\langle \frac{\mu_1 + \mu_2}{2} h \rangle \quad (33)$$

The anisotropy appears in a similar form in the “resistance matrix” :

$$k_x = 12\eta \langle 1/h^3 \rangle; \quad k_y = 12\eta \langle h^3 \rangle^{-1} \quad (34)$$

$$s_x = \frac{1}{\sigma_{el}} \langle 1/h \rangle; \quad s_y = \frac{1}{\sigma_{el}} \langle h \rangle^{-1} \quad (35)$$

$$m_x = \frac{6\eta}{\sigma_{el}} \left\langle \frac{\mu_1 + \mu_2}{h^3} \right\rangle; \quad m_y = \frac{6\eta}{\sigma_{el}} \frac{\langle (\mu_1 + \mu_2) h \rangle}{\langle h \rangle \langle h^3 \rangle} \quad (36)$$

The coefficients describing off-diagonal effects (section III) are then obtained from these matrices expressed in the (e_1, e_2) frame (using equations (11) and (12)) .

F. Discussion

To investigate semi-quantitatively the consequences of the formulas derived above, a simple but insightful example is sinusoidal modulations of the shape and charge density (Figure 5a)

$$h(x) = h_0(1 + \alpha \cos(qx)) \quad (37)$$

$$\mu_1 + \mu_2 = 2(\mu_0 + \delta\mu \cos(qx + \Theta)). \quad (38)$$

Analytical results take a simple form (see Appendix 2) in the limit of weak modulation amplitudes for the shape, which allows to calculate the result through an expansion in α . From this and from inspection of the formulae of the subsection above, a few important points can be derived:

- a simple modulation of the charge pattern is not sufficient to induce off-diagonal effects. This is the consequence of the linear description in terms of the surface charge densities and of the $+/-$ symmetry (see e.g. [9] for a discussion of this)
- a modulation of the shape at homogeneous charge density is enough to produce off-diagonal effects for all phenomenologies (permeation $k_{12} \neq 0$, electro-osmosis and streaming potential/current $m_{12} \neq 0$, conductance $s_{12} \neq 0$). However for a slight modulation $\delta h(x)$ around a mean h_0 , the coupling coefficients will be proportional to $(\delta h/h_0)^2$.
- a correlated coupling of the charge pattern and of the shape leads to stronger $O(\delta h/h_0)$ amplitudes for the off-diagonal electro-hydrodynamic couplings m_{12} and M_{12} . These off-diagonal couplings are proportional to $\delta\mu$, and dominate the longitudinal ones if $\delta\mu/\mu_0 \gg 1$. This synergy between shape and charge modulation stems from the shape-induced symmetry breaking between plus and minus charges, and is described at length in [9] for




FIG. 5. Generation of off-diagonal effects (here electro-osmosis) from a sinusoidal modulation of shape and charge densities. The case depicted here (a) corresponds to $\alpha > 0$, $\delta\mu > 0$, $\Theta = \pi/2$, and a zero average charge density $\mu_0 = 0$. A schematic top view is then used in (b), (c), and (d), with $\theta = \pi/4$. (b): The field E_x generates a flow along x resulting from the opposite action of the narrow positively charged sections (tending to slip the fluid backwards along x) and of the wider negatively charged sections (which induce a slip in the positive direction). The thin sections dominate because of their stronger hydrodynamic resistance so the net flow is opposite to the applied field. (c): A field E_y applied along y induces a stratified flow with thin and wide sections again pushing in opposite directions. As the field is uniform, the slip velocities in the two directions are of similar amplitudes. Thus the net flow is dominated by the wider sections, and points in the direction of the applied field. (d): Thanks to the linearity of the problem, the net flow created by a field E applied along e_2 is obtained by superimposing those obtained in (b) and (c), resulting here in a dominant transverse component.

the specific case of electro-osmosis. A schematic description is given in figure 5.

- extrapolation of these results to the case $\alpha \rightarrow 1$ semi-qualitatively suggests that the off-diagonal components can be of the same order than the diagonal one. Favorable ingredients are a marked shape modulation ($\delta h/h \sim 1$), and a rather contrasted charge modulation ($\delta\mu/\mu_0 \sim 1$).

Indeed, the results of Appendix 2 show that the off-diagonal matrix coefficients ($k_{12}, m_{12}, s_{12}, K_{12}, M_{12}, S_{12}$) are smaller by a factor $\sim \alpha^2$ than their diagonal equivalents if only the shape is modulated ($\delta\mu = 0$). If in addition the charge density is commensurately modulated the off-diagonal electro-hydrodynamic coefficients m_{12} and M_{12} are increased by a factor $\alpha \frac{\delta\mu}{\mu_0} \cos(\Theta)$ relative to their diagonal equivalents.




FIG. 6. A simple heterogeneous geometry to create a vortex (top view). No shape modulation, and a simple charge pattern : a positively charged zone aside a negatively charged one (ideally both plates are patterned in the same way, i.e. floor and ceiling). The rest of the capillary is neutral. The electro-osmotic slip generated by an electric field along the channel leads to a recirculation vortex as shown.

V. CONCLUSION

We have shown that various off-diagonal effects can be generated using micro-patterned geometries allowing for various functionalities: transverse pumping, mixing, flow detection, etc... The corresponding couplings can locally be of same order as the usual (diagonal) electro-kinetic coefficients (sometimes larger). Their actual global value depends on the geometry of the given device (through geometrical ratios such as e.g. L/d). A detailed analysis of the flow geometries (variations in the third (z) direction) and thus of the mixing capabilities will be published elsewhere.

Realization of charge-patterned surfaces at the 10-micron scale has already been experimentally explored in simple geometries [13]. Its combination with shape modulations is clearly within the range of current microfabrication technologies, and is the topic of ongoing studies.

Naturally, more efficient devices for pumping, mixing or flow detection should be realizable by playing with a larger class of patterns, including in particular inhomogeneous ones. A simple example is schematized in Figure 6 where a vortex can be created by application of an electric field. Additional features or control can result from the increase of the third dimension : dealing with thicker fluid layers allows, for example, to produce rolls with axes parallel to the surface [9,13]. Eventually let us stress that although the focus of the present paper is on steady-state effects obtained with d.c. fields, interesting effects are also expected using a.c. fields and arrays of

microelectrodes [3,4,14,15]. This great diversity of geometries imposes a hand-in-hand development of theoretical proposals and experimental realizations that we wish to pursue in the coming years.

Acknowledgments: This work owes much to a continuous interaction with Abe Stroock, and I thank him for his permanent support and for many useful suggestions. Related discussions with Y. Chen, D. Long, A. Pépin and P. Tabeling are gratefully acknowledged.

* Electronic address: armand@turner.pct.espci.fr

- [1] *Micro Total Analysis Systems 2000*, Eds. A. van den Berg, W. Olthuis, P. Bergveld, Kluwer Academic Publishers 2000.
- [2] A.D. Stroock, G. Whitesides, *Physics Today* in press.
- [3] G. Fuhr, T. Schnelle, B. Wagner *J. Micromech. Microeng.*, **4**, 217-226 (1994).
- [4] T. Müller, et al., *Electrophoresis*, **14**, 764-772 (1993).
- [5] M. Washizu, *IEEE transactions on industry applications*, **34**, 732-737 (1998).
- [6] B.S. Gallardo et al., *Science*, **283**, 57-60 (1999).
- [7] D.J. Harrison et al., *Science*, **261**, 895 (1993).
- [8] W.B. Russel, D.A. Saville, W.R. Schowalter, *Colloidal dispersions*, Cambridge University Press, Cambridge 1989.
- [9] A. Ajdari, *Phys. Rev. Lett.*, **75**, 755-758 (1995); A. Ajdari, *Phys. Rev. E*, **53**, 4496-5005 (1996).
- [10] J. Happel, H. Brenner, *Low Reynolds Number Hydrodynamics*, Martinus Nijhoff Publishers, The Hague (1983).
- [11] R.J. Hunter, *Foundations of Colloid Science*, Oxford University Press, New York 1991.
- [12] J.L. Anderson, *Annu. Rev. Fluid Mech.*, **21**, 61-99 (1989).
- [13] A.D. Stroock, et al., *Phys. Rev. Lett.*, **10**, 3314-3317 (2000).
- [14] A. Ajdari, *Phys. Rev. E*, **61**, R45-R48 (2000).
- [15] A.B.D. Brown, C.G. Smith, A.R. Rennie, *Phys. Rev. E*, **63**, 016305 (2001).




FIG. 7. (a): connected electrodes; (b): the continuous electrodes short-circuit potential differences along the channel

APPENDIX 1: WALLS SHORTCUT BY CONNECTED ELECTRODES

We now consider the geometry of section III, but with the walls perpendicular to e_1 now covered by connected electrodes, so as to shortcut any electrostatic potential difference between the two walls.

Our picture here is very simplistic as we do not want to enter the detail of electrochemical reactions. Let us only make the following distinction (Figure 7). First, case (a), we will consider that these walls actually consist of a series of electrode pairs not connected between them, so that although the potential drop is on average zero in the e_1 direction, potential differences can nevertheless exist along the e_2 direction. In the second simplistic case (b), the walls are coated with continuous electrodes in which currents can circulate also along the e_2 direction so that the electrostatic potential is essentially constant $\Delta\phi_1 = \Delta\phi_2 = 0$.

A. Series of connected electrodes

Pressure driven flow - In this geometry (Figure 7a) ($J_{e12} = 0$, $J_1 = 0$, $\Delta\phi_1 = 0$), an applied pressure difference along the channel $\Delta p_2 \neq 0$ results in a streaming potential $\Delta\phi_2$ that differs from the one obtained with passive walls:

$$\Delta\phi_2 = \frac{s_{11}m_{22} - s_{21}m_{12}}{s_{11}k_{22} - m_{12}^2} \Delta p_2 \quad (39)$$

In addition, this pressure drop creates transverse effects: a pressure drop Δp_1 along the e_1 axis that induces recirculation, as well as a *transverse streaming current* $I_1 = LJ_{e11}$ given by:

$$-\Delta p_1 = \frac{d}{L} \frac{s_{11}k_{12} - m_{11}m_{12}}{s_{11}k_{22} - m_{12}^2} \Delta p_2 \quad (40)$$

$$I_1 = LJ_{e11} = \frac{m_{12}}{s_{11}k_{22} - m_{12}^2} \Delta p_2 \quad (41)$$

Electrically driven flow - In the case where no pressure drop exists between the two ends of the channel ($\Delta p_2 = 0$), effects can be generated by applying an electric current $J_{e12} \neq 0$ (or an electric field E_2 along e_2 (due to the short-circuited walls we have $J_1 = 0$, $\Delta\phi_1 = 0$). The applied field creates an electro-osmotic flow along the channel:

$$J_2 = \frac{M_{22}K_{11} - K_{21}M_{12}}{K_{11}} E_2 \quad (42)$$

that is different from the case where the walls were not connected (equation below (18)), if off-diagonal coefficients are non-zero. The electric conduction law is here $J_{e12} = \frac{S_{22}K_{11} - M_{12}^2}{K_{11}} E_2$. *Transverse electro-osmosis* results in a pressure difference $\Delta p_1 = d(M_{12}/K_{11})E_2$ and a total current intensity $I_1 = LJ_{e11} = L \frac{S_{12}K_{11} - M_{12}M_{11}}{K_{11}} E_2$ through the connecting wires.

B. Continuous conducting electrodes

Due to the presence of the electrodes, any potential difference between the entrance and the exit of the channel is short-circuited (i.e. a backward current runs along the electrodes in the e_2 direction) so that $\Delta\phi_2 = 0$ (Figure 7b).

Pressure driven flow - A pressure drop along the channel ($\Delta p_2 \neq 0$) in this situation ($\Delta\phi_2 = 0$, $J_1 = 0$, $\Delta\phi_1 = 0$) again creates a transverse pressure drop across the channel Δp_1 synonymous of recirculation along the e_1 axis, as well as a *transverse streaming current* $I_1 = LJ_{e11}$ given by:

$$-\Delta p_1 = -\frac{d}{L} \frac{K_{12}}{K_{11}} \Delta p_2 \quad (43)$$

$$I_1 = -\frac{M_{12}K_{11} - M_{11}K_{12}}{K_{11}} \Delta p_2 \quad (44)$$

Transverse electro-osmotic pumping - But we can also consider the situation where an electric current J_{e11} is applied between the two walls. Formally, this case ($\Delta\phi_2 = 0$, $J_1 = 0$) allows electro-osmotic pumping in the e_2 direction, even in the absence of a driving pressure gradient in that direction ($\Delta p_2 = 0$). The resulting flow is

$$J_2 = \left(\frac{M_{21}K_{11} - K_{21}M_{11}}{K_{11}} \right) E_1 \quad (45)$$

or $J_2 = (\frac{M_{21}K_{11}-K_{21}M_{11}}{K_{11}S_{11}-M_{11}^2})J_{el1}$. This is simply a manifestation of the transverse electro-osmosis mentioned in the first subsection of this section. It allows the design of lateral electro-osmotic pumps that do not require a global potential difference between the entrance and the exit of the channel (i.e. $\Delta\phi_2$ proportional to L) but rather local potential drops ($\Delta\phi_1$ proportional to d).

APPENDIX 2: SINUSOIDAL MODULATIONS OF SHAPE AND CHARGE DENSITIES

We propose here explicit formulae for the various components of the conductance and resistance matrices, obtained from the lubrication approximation in section (IV), and summarized in IV-E, for the particular case of sinusoidal modulations of the height of the channel $h = h_0(1 + \alpha \cos(qx))$ and of the charge densities $(\mu_1 + \mu_2)/2 = \mu_0 + \delta\mu \cos(qx + \Theta)$.

The lubrication approximation requires that $\alpha h_0 q \ll 1$. We here present explicit formulae that correspond to an expansion in α up to order α^2 , assuming explicitly $\alpha \ll 1$. This provides a useful guide. The results are for the conductance matrix:

$$K_x = \frac{h_0^3}{12\eta}(1 - 3\alpha^2); \quad K_y = \frac{h_0^3}{12\eta}(1 + \frac{3}{2}\alpha^2) \quad (46)$$

$$S_x = \sigma_{el}h_0(1 - \frac{1}{2}\alpha^2); \quad S_y = \sigma_{el}h_0 \quad (47)$$

$$M_x = -\mu_0h_0(1 - \frac{3}{2}\alpha\frac{\delta\mu}{\mu_0}\cos(\Theta) - \frac{1}{2}\alpha^2) \quad (48)$$

$$M_y = -\mu_0h_0(1 + \frac{1}{2}\alpha\frac{\delta\mu}{\mu_0}\cos(\Theta)) \quad (49)$$

and for the resistance matrix

$$k_x = \frac{12\eta}{h_0^3}(1 + 3\alpha^2); \quad k_y = \frac{12\eta}{h_0^3}(1 - \frac{3}{2}\alpha^2) \quad (50)$$

$$s_x = \frac{1}{\sigma_{el}h_0}(1 + \frac{1}{2}\alpha^2); \quad s_y = \frac{1}{\sigma_{el}h_0} \quad (51)$$

$$m_x = \frac{12\eta\mu_0}{\sigma_{el}h_0^3}(1 - \frac{3}{2}\alpha\frac{\delta\mu}{\mu_0}\cos(\Theta) + 3\alpha^2) \quad (52)$$

$$m_y = \frac{12\eta\mu_0}{\sigma_{el}h_0^3}(1 + \frac{1}{2}\alpha\frac{\delta\mu}{\mu_0}\cos(\Theta) - \frac{3}{2}\alpha^2) \quad (53)$$

Thus, the ratios of transverse (12) to longitudinal (11 or 22) coefficients are

$$k_{12}/k_{11} = k_{12}/k_{22} \simeq \frac{9}{2}\alpha^2 \sin \theta \cos \theta \quad (54)$$

$$s_{12}/s_{11} = s_{12}/s_{22} \simeq \frac{1}{2}\alpha^2 \sin \theta \cos \theta \quad (55)$$

$$m_{12}/m_{11} = m_{12}/m_{22} \simeq (-2\alpha\frac{\delta\mu}{\mu_0}\cos \Theta + \frac{9}{2}\alpha^2) \sin \theta \cos \theta \quad (56)$$

$$K_{12}/K_{11} = K_{12}/K_{22} \simeq -\frac{9}{2}\alpha^2 \sin \theta \cos \theta \quad (57)$$

$$S_{12}/S_{11} = S_{12}/S_{22} \simeq -\frac{1}{2}\alpha^2 \sin \theta \cos \theta \quad (58)$$

$$M_{12}/M_{11} = M_{12}/M_{22} \simeq (-2\alpha\frac{\delta\mu}{\mu_0}\cos \Theta - \frac{1}{2}\alpha^2) \sin \theta \cos \theta \quad (59)$$

where terms of order $\alpha^2(\frac{\delta\mu}{\mu_0})^2$ have been omitted in the equations for m_{12} and M_{12} . Actually, if the average

charge is almost zero so that $\delta\mu/\mu_0$ is very large, then in the limit $\alpha\frac{\delta\mu}{\mu_0} \gg 1$, equations (56) and (59) become:

$$m_{12}/m_{11} \simeq M_{12}/M_{11} \simeq \frac{4 \sin \theta \cos \theta}{3 \cos^2 \theta - \sin^2 \theta} \quad (60)$$

so that longitudinal effects are totally dominated by transverse ones for a “magic angle” $\theta = \pi/3$.